

**Features:**

- ❖ Connect with 4-Pin gooseneck microphone to be a desktop conference microphone
- ❖ Built-in high-sensitivity condenser microphone that can be independently used as a boundary microphone
- ❖ The back panel has a balanced XLR connector for any mixer supplying phantom power and a switch to select the audio source from either the inner boundary microphone or the optional gooseneck microphone
- ❖ Features a TALK / MUTE button. When pushing the button to talk, the green indicator on the base and LED ring indicator on mic will light up



**Specifications:**

Model	GEN-GM18
<b>Base Unit</b>	
Input Jack	4-Pin XLR Female
Output Jack	Balanced XLR Male
Power Supply	External DC 24 – 52 V phantom power is required
<b>Gooseneck Microphone</b>	
Capsule	10mm unidirectional condenser microphone
Frequency Response	20 Hz – 20 kHz
SNR	64dB-A
Sensitivity	-46 ± 3 dBV / Pa (0 dB = 1 V / Pa)
Max. SPL	142 dB
Output Jack	4-Pin XLR male
Length	410 mm or 500 mm or 600 mm
Indicator	Red LED ring indicator

\*Picture for illustration purpose only